

STEINER MP5 MICRO PISTOL SIGHT

STEINER 
Nothing Escapes You



**INSTRUCTION
MANUAL**

English

CONTENTS**PAGE**

General introduction	3
MPS description	4
Operation	6
MPS mounting	7
Mounting on weapon-specific adapters	8
General information about the MPS	9
Elevation and windage adjustment	9
Zeroing	9
Illumination	10
Programming	10
Environmental conditions	11
Technical data	12
Disposal	13

INTRODUCTION

The new Steiner MICRO PISTOL SIGHT embodies everything professionals expect in the field - and more. Developed from real-world experience and extreme situations, every detail has been specifically refined to take performance, safety, and ease of operation to a new level.

MPS DESCRIPTION



- ① Battery compartment
- ② Illumination buttons (+ und -)
- ③ Elevation adjustment
- ④ Windage adjustment
- ⑤ Mounting screw

- ⑥ Tool

OPERATION

The MPS is powered by a standard 3V lithium battery (CR2032). To insert or replace the battery, unscrew the battery compartment cover using the supplied tool. Make sure that the positive pole of the battery faces upward when inserted and that the contacts are clean. Then screw the cover back on without overtightening it. The MPS can now be switched on using the illumination button ②.



MPS MOUNTING

Loosen the mounting screw so that the clamp opens far enough, place the MPS on the mount, push the MPS forward before tightening, check that it is seated correctly, and then tighten to max. 2.16 Nm.

REPLACING THE BATTERY FOR RETICLE ILLUMINATION

The MPS is powered by a standard lithium battery (CR2032 3V).

1. Unscrew the cover of the battery compartment using the special tool.
2. Remove the old battery and insert the new battery.
3. Positive battery side is facing upwards when inserting it.
4. Screw the battery compartment lid back on (do not overtighten).
5. The MPS can now be switched on with the illumination control.

Battery is removed by applying hand recoil on a flat surface



MOUNTING ON WEAPON-SPECIFIC ADAPTERS

It is possible to mount the MPS on pistols that have a cutout for an RDO optic. Weapon-specific compatible adapters are available on the market. These must be mounted on the pistol according to the enclosed instructions. Here, too, it is recommended to protect the adapter against corrosion with oil or grease. Then loosen the mounting screw on the MPS, place the MPS on the adapter, push the MPS forward before tightening, and tighten to max. 2.16 Nm.

GENERAL INFORMATION ABOUT THE MPS

ELEVATION AND WINDAGE ADJUSTMENT

Elevation and windage can be adjusted precisely. The elevation adjustment screw is located on top of the MPS; the windage adjustment screw is located on the right-hand side.

ZEROING

Adjust the point of aim using the supplied tool. The direction for moving the point of aim is indicated on the adjustment screws. One scale unit/click corresponds to 1 MOA or 2.9 cm at 100 m. The parallax is fixed at 25 m.

ILLUMINATION

A total of 8 levels: 6 day/night levels and 2 for night-vision devices. Adjustable using +/- . By pressing both buttons simultaneously, it is possible to save the setting. The setting can only be changed again after pressing +/- simultaneously once more.

MPS PROGRAMMING

It is recommended to perform programming with your thumbs, as it takes some effort to press and hold both buttons. This is intentional to prevent the user from performing this action accidentally.

DEACTIVATING THE AUTOMATIC 15-HOUR SHUTOFF

Press and hold the „+“ and „-“ buttons simultaneously for 10 seconds. The illuminated dot flashes slowly 5 times to indicate that the programming has been accepted.

- It is recommended to do this at a high brightness level so that the user can easily see the dot flashing.
- Repeat the process to activate the Auto-Off function; after about 10 seconds, the illuminated dot flashes quickly 15 times as confirmation.
- **Please note:** If you deactivate the Auto-Off function, the highest brightness level is also deactivated in order to optimize battery life.


DEACTIVATING THE BUTTON LOCK

Press and hold the two buttons „+“ and „-“ simultaneously for 3 seconds.


- This locks all button functions.
- Repeat the process to unlock the button lock again.

ENVIRONMENTAL CONDITIONS

The MPS is pressure-waterproof. Dust, rain, and snow cannot harm it. The MPS remains operational even after being immersed in water. However, if the MPS has come into contact with dirty or salty water, rinse it with distilled water and then dry it with a soft optics cloth.



2 MOA



3,3 MOA

TECHNICAL DATA

MPS Micro Pistol Sight Item no. 8700000040 (3.3 MOA)	
MPS Micro Pistol Sight Item no. 8700000042 (2 MOA)	
Magnification	1 x
Effective objective	21 mm x 16 mm
Adjustment steps	1 click = 1 MOA
Elevation adjustment range	90MOA (50Mil)
Windage adjustment range	90MOA (50Mil)
Battery	CR 2032
Battery life	90.000 h (medium brightness)
Auto-off	15 h
Aiming dot color	Red
Aiming dot diameter	Ø 3,3 MOA / 2 MOA
Illumination control	8 levels, 6 day/night and 2 night-vision-device modes, switchable via +/- . By pressing both buttons simultaneously, it is possible to lock/unlock the setting.
Pressure-waterproof	Yes
Operating temperature	-40 °C - +60 °C
Storage temperature	-40 °C - +63 °C
Weight without adapter	66 g
Dimensions	45 x 31,6 x 31,9 mm
Height between base and optical center	12,5 mm
Parallax compensation	Fixed at 25 m

DISPOSAL OF ELECTRICAL AND ELECTRONIC EQUIPMENT

(applies to the EU, and other European countries with separate collection systems)

User information on the disposal of electrical and electronic equipment (private households).



This symbol on our products and/or accompanying documents means that used electrical and electronic products should not be mixed with unsorted municipal waste (ordinary household waste). For proper treatment, recovery and recycling, take these products to the appropriate collection points where they will be accepted without charge.

Before handing over the waste equipment to a collection point, please remove used batteries and accumulators and dispose of them separately from the waste equipment at the appropriate collection points.

In some countries, it may also be possible to dispose of these products at your local retailer when purchasing an equivalent new product.

Proper disposal of this product will help protect the environment and prevent potential harm to people and the environment which could result from inappropriate waste handling.

For more detailed information on the nearest collection point, please contact your local government. In accordance with provincial legislation, penalties may be imposed for improper disposal of this type of waste.

For business customers in the European Union

Please contact your dealer or supplier if you wish to dispose of electrical and electronic equipment. He will have more information for you.

Information on disposal in other countries outside the European Union

This symbol is only valid in the European Union. Please contact your local council or distributor if you wish to dispose of this product and ask for a disposal option.



Item Number V0000783 05/2026

STEINER-OPTIK GmbH
Dr.-Hans-Frisch-Str. 9
D-95448 Bayreuth

INTERNATIONAL:
www.steiner.de

USA:
www.steiner-optics.com

DEFENSE:
www.steiner-defense.com